



MV Central inverters

R10000TL

1.000kW - 1.000V

Technical data

Type code	R10000TL	
MPPT voltage range (V _{dc})	675 - 1.000 V	
Absolute max DC voltage (V _{dc})	1.100 V	
DC-voltage ripple (%)	<2%	
Maximum input current (A _{dc})	1.600 A	
DC control mode	Rapid and efficient MPPT control	
Number of MPPT	1	
Reverse Polarity Protection	•	
DC input connection	Integrated DC Switch	
Overvoltage Protection	SPD varistor device Class II (Opt. Class I+II)	
AC Output grid		
Max Power (kW) ¹⁾	1.025 kW @ 25°C	1.000 kW @ 50°C
Max Apparent Power Smax (kVA)	1.025 kVA @ 25°C	1.000 kVA @ 50°C
Maximum Current (A _{ac}) ¹⁾	1.575 A @ 25°C	1.480 A @ 50°C
Max unbalance current	< 2%	
AC output Voltage (V _{ac})	400 V _{RMS} ±10%	
Nr. Phase	3-phase (L1 – L2 – L3 – PE)	
Frequency (Hz)	50/60 Hz	
Aux. power supply (V _{ac} - I _{ac})	230V ±10% - 16A (L-N)	
Auxiliary control supply (V _{ac} - I _{ac})	230V ±10% - 10A (L-N)	
Distortion factor (THDi) ²⁾	<3%	
Power Factor ³⁾	From 0 to 1 inductive or capacitive	
Galvanic insulation	No (transformerless)	
AC input connection	Magnetothermic circuit breaker	
General Data		
Maximum efficiency	98.80%	
European efficiency	98.30%	
Static MPPT efficiency	> 99.9 %	
Dynamic MPPT efficiency	> 99.8 %	
Night consumption (W)	< 60 W	
Weight (kg)	1.670 kg	
Protection degree	IP20 (Opt.31)	
Cooling	By using fans speed controlled by temperature	
Dimensions (W x D x H)	1.750x825x2.235 mm	
Noise level (dBA)	< 70 dBA	
Operating temperature (°C) ⁴⁾	-10° C +53° C	
Storage temperature (°C)	-20° C +60° C	
Humidity (Not condensing) (%)	0 ÷ 95%	
Height above the sea (without derating) ⁵⁾	1.500 m	
Air Flow	4.850 m³/h	
Overvoltage Category	II	
Color	RAL 9006	

1) Power factor (cosφ)= 1 and Vac nominal.

2) THDi is lower than 3% for inverter power greater than 25%.

3) P-Q capability is semicircular with radius equal to S_{max} for all MPPT range.

4) From 45°C to 53°C derating of power.

5) Above 1.000m a.s.l. derating of the power of 1% per 100 m.

Note: Each inverter must be connected separately to its own LV/MV transformer or it has to be connected to a separate LV secondary input of the LV/MV transformer. Two or more inverters cannot be connected in parallel to the same LV secondary input of the LV/MV transformer.

Remark. Features not specifically listed in the present data sheet are not included in the product



For more information please contact your local FIMER representative or visit:

We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. FIMER does not accept any responsibility whatsoever for potential errors or possible lack of information in this document.

We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilization of its contents – in whole or in parts – is forbidden without prior written consent of FIMER. Copyright© 2020 FIMER. All rights reserved.

